



6.1 It Fuel Tank



Socket Panel



Honda GX390 Engine



Stage V

We offer now what others will do tomorrow.



### Genset s.p.a.

Via Stazione 5 - 27030 Villanova d'Ardenghi (PV) - Italy Phone:+39-0382-5091

commerciale@genset.it www.genset.it



# GenSet Next Gen technology for top business.

### MG 8000 I-HE 6,1 lt / TECHNICAL DATA

PORTABLE SINGLE-PHASE POWER GENERATOR OUTPUT POWER 7 kVA PETROL ENGINE 3000 RPM FUEL TANK 6,1 LT

#### Standard Features

- · Low oil level shutdown device
- I x 32 A, 230 V 50 Hz single-phase EEC socket
- $\bullet$  I x 16 A, 230 V 50 Hz single-phase EEC socket
- 12 Vdc battery charger outlet protected by fuse
- Protections for power outputs
- Earth Leakage Circuit Breaker (ELCB)

### Options available as factory options

- Versions with different voltages
- 60Hz version
- Automatic voltage regulator (AVR)

# Accessories on request

Trolley: two-wheels and handles

### Noise level

• Lwa 97 (72 dB a 7 mt)

#### AC generator - 50Hz

- Type: synchronous
- Single-phase power (max.): 7 kVA 230 V
- Battery charger power: I20 W I2V I0 A DC
- Power Factor: cos φ 0,8

## Petrol Engine 3000 rpm

- Type: Honda GX 390 OHV 1 cyl. STAGEV 11 HP (8,2 kWm) 390 cm<sup>3</sup>
- · Cooling system: air
- Starting system: recoil
- Fuel tank capacity: 6,1 lt
- Fuel consumption @ 75%: 3,3 lt/h

#### Other features

- Insulation Class: H
- Ambient temperature: 40 °C (\*)
- Altitude: 1000 mt (\*)
- Mechanical Protection: IP 23
- Dimensions (L  $\times$  W  $\times$  H): 770  $\times$  480  $\times$  625 mm
- Dry weight: 78 kg